

# Datasheet

## Audio indoor station with handset



Lux2 indoor station

Communication possibilities	
Voice transmission	Duplex communication with handset
Audio privacy function	Yes
Automatic call cut-off	Yes
Number of selectable ring tones	13
Speaking time	Max. 2 min
Functions and adjustable parameters	
Functions through keys/handset	Light switch, accept conversation, door release, ring tone mute, control function, ring tone and conversation volume, ring tone selection.
Parameters adjustable with Service Device	Light switch function, parallel call.
Parameters adjustable with Configo™	Parallel call, ring tone selection, change AS-address, reset to factory settings function.
Initial setup (connect doorstation button with indoor station)	With Service device or Manually
Housing	
Size	180 x 100 x 45 mm (handset length 205 mm)
Recommended mounting height of display	160 cm
Mounting	Surface-mount
Material and color	Plastic, white
Handset cradle	Magnetic
Handset cord	Pluggable
Weight	340 g
Dock station available	Yes
Technical data	
Signal transmission and power supply	Polarity-free and short-circuit protected 2-wire BUS
Wiring technique (number of wires)	2 (a,b) or 3 (a, b, P)
Power supply	24 V DC
Input current I(a)	I(a) = 0.2 mA
Input current I(P), standby	I(P) = 0,8 mA
Input current I(Pmax), max.	I(Pmax)= 70 mA
Mixed installation with audio and video in a system	Possible
Compatible with access control and Nova Software	Yes
Acceptable ambient temperature	-5 to + 40 °C
UV resistance	Unlimited



Lux2 desktop holder

Desktop holder (ZIT3030-0010)	
Material	Aluminium, anodized
Size (mm)	H 168 x W 86 x D 27
Weight	225 g (without cable)
Cable	Connection cable (3 m long)
Screws	3 x Lens head screw